


Model 7192

High-speed synchronizer and distribution PMC/XMC module

Synchronizes up to four Cobalt, Onyx, or Jade I/O boards

- Synchronizes sampling and data acquisition for multichannel systems
- Synchronizes gating and triggering functions
- Clock rates up to 1.8 GHz
- Front panel MMCX connectors for input signals



The Model 7192 High-Speed Synchronizer and Distribution Board synchronizes multiple Cobalt, Onyx, and Jade modules within a system. It enables synchronous sampling and timing for a wide range of multichannel high-speed data acquisition, DSP, and software radio applications.

Up to four modules can be synchronized using the 7192, with each receiving a common clock along with timing signals that can be used for synchronizing, triggering and gating functions. Model 7192 is compatible with the products listed in [Supported Products](#).


INPUT SIGNALS

Model 7192 provides three front panel MMCX connectors to accept input signals from external sources: one for clock, one for gate or trigger and one for a synchronization signal. Clock signals can be applied from an external source such as a high performance sine-wave generator. Gate/trigger and sync signals can come from an external system source. In addition to the MMCX connector, a reference clock can be accepted through the first front panel μ Sync output connector, allowing a single Cobalt, Onyx, Flexor, or Jade board to generate the clock for all subsequent boards in the system.

OUTPUT SIGNALS

The 7192 provides four front panel μ Sync output connectors, compatible with a range of high-speed Cobalt, Onyx, Flexor, and Jade boards. The μ Sync signals include a reference clock, gate/trigger and sync signals and are distributed through matched cables, simplifying system design.

BLOCK DIAGRAM



GATE AND SYNCHRONIZATION SIGNALS

The 7192 features separate inputs for gate/trigger and sync signals. A programmable delay allows the user to make timing adjustments on the gate/trigger and sync signals before they are sent to buffers for output through the μ Sync output connectors.

CLOCK SIGNALS

The 7192 can accept a user-supplied external clock on its front panel MMCX connector. As an alternative to the external clock, the 7192 can use its on-board programmable voltage controlled crystal oscillator (VCXO) as the clock source. The VCXO can operate alone or be locked to a system reference clock signal delivered to the front panel reference clock input.

The external or on-board clock can operate at full rate or be divided and used to register all sync and gate/trigger signals as well as providing a reference clock to all connected boards. In addition, the clock is available at the Clock Out MMCX as a sample or reference clock for other boards in the system.

CALIBRATION

The 7192 features a calibration output specifically designed to work with the 71640/41, 71741 and 71841 3.6 GHz A/D XMC modules to provide a signal reference for phase adjustment across multiple A/Ds.


PROGRAMMING

The 7192 allows programming of operating parameters including: VCXO frequency, clock dividers, and delays that allow the user to make timing adjustments on the gate and sync signals. These adjustments are made before they are sent to buffers for output through the μ Sync connectors.

The 7192 is programmed via a TWSI control interface on the first μ Sync connector. The control interface is compatible with the front panel μ Sync connectors of all high-speed Cobalt, Onyx, and Jade modules, thereby providing a single cable connection that carries both control and timing signals.

FRONT PANEL CONNECTIONS

The front panel includes four μ Sync input/output connectors, four MMCX connectors, and two LEDs. Note that the μ Sync output connectors are custom-wired and NOT compatible with standard μ HDMI cables. Use the cables described in Accessories.



- **Synchronization In/Out:** A μ Sync 19-pin connector, labeled **SYNC I/O**, provides a reference clock input and TWSI control input; and sync, reference clock, and gate outputs for synchronizing multiple boards. This connector includes TWSI (I2C) bus pins which allow a Cobalt, Onyx, or Flexor board to control the 7192.
- **Synchronization Outputs:** Three front-panel μ Sync 19-pin connectors, labeled **SYNC 2 OUT**, **SYNC 3 OUT**, and **SYNC 4 OUT**, provide sync, reference clock, and gate outputs for synchronizing multiple Cobalt, Onyx, or Flexor boards.
- **Sample Clock / Reference Input:** An MMCX connector, labeled **CLK IN**, is used for a sample clock or reference input.
- **Clock Present LED:** A green LED labeled **CLK PR** illuminates when the sample clock is working.
- **Gate/Trigger Input:** An MMCX connector, labeled **GATE IN**, is used for a gate/trigger LVTTTL input (do not exceed 3.3V).
- **SYNC Input:** An MMCX connector, labeled **SYNC IN**, is used for a sync LVTTTL input (do not exceed 3.3V).
- **Power LED:** A green LED labeled **PWR** illuminates when a +5VDC is applied to the board.
- **Clock/Calibration Output:** An MMCX connector, labeled **CAL OUT** is used for clock/calibration output.

SUPPORTED PRODUCTS

The 7192 supports the following Jade, Onyx, and Cobalt products:

- Jade models 71131, 71132, 71141, and 71841
- Onyx models 71730 and 71741
- Cobalt models 71630, 71640, 71641, 71670, 71671

SOFTWARE

If you are using a Cobalt, Onyx, or Flexor board in conjunction with 7192, software support is provided by Mercury's ReadyFlow® Board Support Packages (BSP). There is a ReadyFlow BSP to support 7192 and a separate ReadyFlow BSP to support the Cobalt, Onyx, or Flexor board.

If you are using a Jade board in conjunction with 7192, software support is provided by Mercury's Navigator® Board Support Package (BSP). In addition to supporting the Jade board, Navigator BSP supports 7192 via the I2C interface on the Jade board.

SPECIFICATIONS

Front Panel Sample Clock/Reference Input

Connector Type: MMCX
 Input Impedance: 50 ohms
 Input Level: 0 dBm to +10 dBm, sine wave
 Sample Clock Frequency: 100 MHz to 2 GHz
 Reference Frequency: 5 to 100 MHz

Front Panel Gate/Trigger & Sync Inputs

Connector Type: MMCX
 Input Level: LVTTTL

Front Panel μ Sync Inputs/Outputs

Quantity: 4
 Connector Type: 19-pin μ HDMI
 Signal Level: CML
 Signals (μ Sync connector 1): Reference Clock In, TWSI control In, Reference Clock Out, Gate/Trigger Out, Sync Out
 Signals (μ Sync connectors 2-4): Reference Clock Out, Gate/Trigger Out, Sync Out

Front Panel Clock / Calibration Output

Connector Type: MMCX
 Output Impedance: 50 ohms
 Output Level: +6 dBm nominal, sine wave
 Sample Clock Frequency: 100 MHz to 1.8 GHz

Programmable VCXO

Frequency Ranges: 10-945 MHz, 970-1134 MHz, and 1213-1417.5 MHz
 Tuning Resolution: 32 bits
 Unlocked Accuracy: ± 20 ppm

PLL, Divider & Jitter Cleaner

Type: Texas Instruments CDCM7005

Frequency Dividers: 1, 2, 3, 4, 6, 8 and 16

PMC/XMC Interface

Power only on PMC P1 or XMC P15

Environmental

Operating Temp: 0° to 50° C

Storage Temp: -20° to 90° C

Relative Humidity: 0 to 95%, non-cond.

Size

Standard PMC module: 2.91 in. x 5.87 in.

ACCESSORY PRODUCTS

Model	Description
	4 ea. 18" µSync cables are supplied; additional cables may be ordered:
2192-018	µSync cable - 18"
2192-036	µSync cable - 36"

ORDERING INFORMATION

Model	Description
7192	High-Speed Synchronizer and Distribution Board - PMC/XMC

**Corporate Headquarters**

50 Minuteman Road
Andover, MA 01810 USA

+1 978.967.1401 tel

+1 866.627.6951 tel

+1 978.256.3599 fax

International Headquarters**Mercury International**

Avenue Eugène-Lance, 38
PO Box 584

CH-1212 Grand-Lancy 1

Geneva, Switzerland

+41 22 884 5100 tel

Learn more

Visit: mercy.com/go/MP7192

For technical details, contact:

mercy.com/go/CF7192



The Mercury Systems logo is a registered trademark of Mercury Systems, Inc. Other marks used herein may be trademarks or registered trademarks of their respective holders. Mercury products identified in this document conform with the specifications and standards described herein.

Conformance to any such standards is based solely on Mercury's internal processes and methods. The information contained in this document is subject to change at any time without notice.

