

Low-Pass Filter X3906



Specifications are subject to change without notice

Specifications (+25°C)

Parameter	Value
Passband	1 to 8000 MHz
Insertion Loss	1.0 dB
VSWR	2:1
Rejection	50 dB from 9500 to 10500 MHz
Rejection	65 dB from 10501 to 20000 MHz
Connectors	SMA Female
Package Size	0.5" x 0.9" x 5.0"

Need More Help? Need a Variant of This Product?

Contact Mercury's RF & Microwave engineering team at rf.microwave@mrcy.com or visit www.mrcy.com/rf for a detailed listing of RF and Microwave products.



Corporate Headquarters • 50 Minuteman Road • Andover, MA 01810 USA • (978) 967-1401 • (866) 627-6951 • Fax (978) 256-3599 • www.mrcy.com

6788.00E-0718-SS-X3906-filter